


## Low Dropout Voltage Regulator

### ■ GENERAL DESCRIPTION

The NJM2871B/72B are low dropout voltage regulator designed for cellular phone applications.

Advanced Bipolar technology achieves low noise, high ripple rejection and low quiescent current.

### ■ PACKAGE OUTLINE





NJM2871BF/72BF


### ■ FEATURES

- High Ripple Rejection      75dB typ. ( $f=1\text{kHz}$   $V_o=3\text{V}$  version)
- Output Noise Voltage       $V_{no}=30\mu\text{VRms}$  typ. ( $C_p=0.01\mu\text{F}$ )
- Output capacitor with  $1.0\mu\text{F}$  ceramic capacitor ( $V_o \geq 2.7\text{V}$ : Version)
- Output Current               $I_o(\text{max.})=150\text{mA}$
- High Precision Output       $V_o \pm 1.0\%$
- Low Dropout Voltage         $0.10\text{V}$  typ. ( $I_o=60\text{mA}$ )
- Input Voltage Range         $+2.3 \sim +14\text{V}$  ( $V_o \leq 2.0\text{V}$  version)
- ON/OFF Control            (Active High)
- Internal Short Circuit Current Limit
- Internal Thermal Overload Protection
- Bipolar Technology
- Package Outline            SOT-23-5 (MTP5)

### ■ PIN CONFIGURATION



### ■ EQUIVALENT CIRCUIT



# NJM2871B/72B

www.DataSheet4U.com

## ■ OUTPUT VOLTAGE RANK LIST

Device Name	V <sub>OUT</sub>	Device Name	V <sub>OUT</sub>	Device Name	V <sub>OUT</sub>
NJM287*BF15	1.5V	NJM287*BF26	2.6V	NJM287*BF34	3.4V
NJM287*BF18	1.8V	NJM287*BF27	2.7V	NJM287*BF35	3.5V
NJM287*BF19	1.9V	NJM287*BF28	2.8V	NJM287*BF38	3.8V
NJM287*BF02	2.0V	NJM287*BF29	2.9V	NJM287*BF04	4.0V
NJM287*BF21	2.1V	NJM287*BF03	3.0V	NJM287*BF48	4.8V
NJM287*BF23	2.3V	NJM287*BF31	3.1V	NJM287*BF05	5.0V
NJM287*BF24	2.4V	NJM287*BF32	3.2V		
NJM287*BF25	2.5V	NJM287*BF33	3.3V		

## ■ ABSOLUTE MAXIMUM RATINGS

(Ta=25°C)

PARAMETER	SYMBOL	RATINGS		UNIT
Input Voltage	V <sub>IN</sub>	+14		V
Control Voltage	V <sub>CONT</sub>	+14(*1)		V
Power Dissipation	P <sub>D</sub>	SOT-23-5	350(*2) 200(*3)	mW
Operating Temperature	T <sub>OPR</sub>	-40 ~ +85		°C
Storage Temperature	T <sub>STG</sub>	-40 ~ +125		°C

(\*1) : When input voltage is less than +14V, the absolute maximum control voltage is equal to the input voltage.

(\*2) : Mounted on glass epoxy board based on EIA/JEDEC. (114.3x76.2x1.6mm: 2Layers)

(\*3) : Device itself

## ■ Operating voltage

V<sub>IN</sub>=+2.3 ~ +14V (In case of Vo<2.1V version)

## ■ ELECTRICAL CHARACTERISTICS

(V<sub>IN</sub>=Vo+1V, C<sub>IN</sub>=0.1μF, C<sub>O</sub>=1.0μF: Vo≥2.7V (C<sub>O</sub>=2.2μF : 1.8V<Vo≤2.6V; C<sub>O</sub>=4.7μF : Vo≤1.8V), C<sub>P</sub>=0.01μF, Ta=25°C)


PARAMETER	SYMBOL	TEST CONDITION	MIN.	TYP.	MAX.	UNIT
Output Voltage	Vo	I <sub>O</sub> =30mA	-1.0%	-	+1.0%	V
Quiescent Current	I <sub>Q</sub>	I <sub>O</sub> =0mA, except I <sub>CONT</sub>	-	120	180	μA
Quiescent Current at Control OFF	I <sub>Q(OFF)</sub>	V <sub>CONT</sub> =0V	-	-	100	nA
Output Current	I <sub>O</sub>	Vo=0.3V	150	200	-	mA
Line Regulation	ΔVo/ΔV <sub>IN</sub>	V <sub>IN</sub> =Vo+1V ~ Vo+6V, I <sub>O</sub> =30mA	-	-	0.10	%/V
Load Regulation	ΔVo/ΔI <sub>O</sub>	I <sub>O</sub> =0 ~ 100mA	-	-	0.03	%/mA
Dropout Voltage (*4)	ΔV <sub>I-O</sub>	I <sub>O</sub> =60mA	-	0.10	0.18	V
Ripple Rejection	RR	ein=200mVrms, f=1kHz, I <sub>O</sub> =10mA, Vo=3V version	-	75	-	dB
Average Temperature Coefficient of Output Voltage	ΔVo/ΔT <sub>A</sub>	T <sub>A</sub> =0 ~ +85°C, I <sub>O</sub> =10mA	-	±50	-	ppm/°C
Output Noise Voltage	V <sub>NO1</sub>	f=10Hz~80kHz, I <sub>O</sub> =10mA, Vo=3V Version	-	30	-	μVrms
Control Voltage for ON-state	V <sub>CONT(ON)</sub>		1.6	-	-	V
Control Voltage for OFF-state	V <sub>CONT(OFF)</sub>		-	-	0.6	V

(\*4): The output voltage excludes under 2.1V.

The above specification is a common specification for all output voltages.

Therefore, it may be different from the individual specification for a specific output voltage.

## ■ TEST CIRCUIT




\*5 1.8V <  $V_o$  ≤ 2.6V version :  $C_o=2.2\mu F$   
 $V_o \leq 1.8V$  version :  $C_o=4.7\mu F$

# NJM2871B/72B

www.DataSheet4U.com


## ■ TYPICAL APPLICATION

- ① In the case where ON/OFF Control is not required:



Connect control terminal to  $V_{IN}$  terminal

- ② In use of ON/OFF CONTROL:



State of control terminal:

- "H" → output is enabled.
- "L" or "open" → output is disabled.

### \*Noise bypass Capacitance $C_p$

Noise bypass capacitance  $C_p$  reduces noise generated by band-gap reference circuit. Noise level and ripple rejection will be improved when larger  $C_p$  is used. Use of smaller  $C_p$  value may cause oscillation.


Use the  $C_p$  value of  $0.01\mu F$  greater to avoid the problem.

### \*In the case of using a resistance "R" between $V_{IN}$ and control.

The current flow into the control terminal while the IC is ON state ( $I_{CONT}$ ) can be reduced when a pull up resistance "R" is inserted between  $V_{IN}$  and the control terminal.

The minimum control voltage for ON state ( $V_{CONT(ON)}$ ) is increased due to the voltage drop caused by  $I_{CONT}$  and the resistance "R". The  $I_{CONT}$  is temperature dependence as shown in the "Control Current vs. Temperature" characteristics. Therefore, the resistance "R" should be carefully selected to ensure the control voltage exceeds the  $V_{CONT(ON)}$  over the required temperature range.







## ■ POWER DISSIPATION vs. AMBIENT TEMPERATURE









# NJM2871B/72B

www.DataSheet4U.com

## ELECTRICAL CHARACTERISTICS









## ELECTRICAL CHARACTERISTICS








# NJM2871B/72B

www.DataSheet4U.com

## ELECTRICAL CHARACTERISTICS







## ELECTRICAL CHARACTERISTICS



# NJM2871B/72B

www.DataSheet4U.com

## ELECTRICAL CHARACTERISTICS



**[CAUTION]**  
The specifications on this databook are only given for information, without any guarantee as regards either mistakes or omissions. The application circuits in this databook are described only to show representative usages of the product and not intended for the guarantee or permission of any right including the industrial rights.