

SPECIFICATION SHEET

JFW MODEL 50RF-038

RF FUSEHOLDER

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Frequency Range DC-1000 MHz

Impedance 50 Ohms nominal

VSWR 1.5:1 maximum DC-500 MHz
1.6:1 maximum 500-1000 MHz
(with 1/16 Amp fuse)

1.2:1 maximum DC-500 MHz
1.4:1 maximum 500-1000 MHz
(with 1/8 or 1/4 Amp fuse)

Insertion Loss 2.0 dB maximum (1/16 Amp fuse)
0.5 dB maximum (1/8 Amp fuse)
0.3 dB maximum (1/4 Amp fuse)

RF Fusing Level +23 dBm (195 mW) (1/16 Amp fuse)
+29 dBm (785 mW) (1/8 Amp fuse)
+35 dBm (3.13 W) (1/4 Amp fuse)

Fuse Rating At 100% of rated current:
4 hours minimum

At 200% of rated current:
1/16 A 1 sec max (0.015 sec typical)
1/8 A 1 sec max (0.04 sec typical)
1/4 A 1 sec max (0.1 sec typical)

RF Connector BNC male/female

Physical Size See outline drawing 092-5140

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	11/15/2006		CLK 11/15/2006				