

by Honeywell

Description

The Fire Control Instruments Model PTR-2 narrow carriage, 9-pin dot matrix printer is designed to work with the various FCI fire alarm control panels. This printer will furnish a printed record of all events occurring in the system. Small and compact, the PTR-2 printer is the ideal supplement to the FCI fire alarm system.

Installation

The PTR-2 is simple to install. The unit must be plugged in to a local 120 VAC power source. A factory-furnished cable is plugged into the printer and the other end is plugged into the printer port of the FCI fire alarm control panel.

Note: The PTR-2 operates on 120 VAC only. For operation during a power failure, we recommend use of an uninterruptible power supply (UPS).

Paper Type

Max. Media Size: A4 (8.25 in x 11.7 in.)
Media Type: Continuous forms, perforated plain paper, plain paper

Specifications

Input	120 VAC, 60 Hz
Power	90 watts (Operational) 10 watts (Stand By)
I/F Type	RS-232C
Baud Rate:	
7100	9,600 bits/second
7200	1,200 bits/second
Operating Temperature	50° to 95° F (10° to 35° C)
Relative Humidity	20 - 80%
Dimensions	7.8" H x 16.8" W x 8.5"D (19.8 H x 42.7 W x 21.6 D cm)
Weight	10.8 lbs. (4.9 kg)

Dot Matrix Printer



PTR-2

Features

- Supervised Operation.
- High Speed Printing.
- Compact Design.
- Correspondence Quality Print.
- Simple Installation.
- Low Noise Level.
- Ergonomic Design.

Ordering Information

Model	Description
PTR-2	Dot Matrix Printer

E3 Series™ is a trademark of FCI.

GAMEWELL-FCI

12 Clintonville Road, Northford, CT 06472 - Tel: (203) 484-7161 - Fax: (203) 484-7118

Specifications are for information only, are not intended for installation purposes, and are subject to change without notice. No responsibility is assumed by Gamewell-FCI for their use.

©2006 Gamewell-FCI All rights reserved.

www.gamewell-fci.com

9020-0550 Rev. B page 1 of 1