



SPECIFICATIONS

FREQUENCY RANGE: DC TO 18 GHz
 IMPEDANCE: 50 OHMS
 INSERTION LOSS: 6 dB NOMINAL
 INPUT POWER: 1 WATT AVERAGE
 AMPLITUDE TRACKING: .5 dB
 TEMPERATURE RANGE: -65°C TO $+125^{\circ}\text{C}$
 PHASE TRACKING: $\pm 3^{\circ}$
 MAX INPUT VSWR: 1.35:1
 OUTPUT PORT ARE SYMMETRICAL TO MALE INPUT



PASTERNAK ENTERPRISES, INC.

P.O BOX 16759, IRVINE, CA 92623
 PHONE (949) 261-1920 FAX (949) 261-7451

WEB ADDRESS: www.pasternack.com
 E-MAIL ADDRESS: sales@pasternack.com

COAXIAL & FIBER OPTICS

DWG TITLE

PE2066

DES.

N FEMALE-MALE-FEMALE RESISTIVE POWER
 DIVIDER, FREQUENCY RANGE: DC TO 18 GHz

REV. B

FSCM NO. 53919

CAD FILE

SCALE N/A

SIZE A

127

NOTES:

1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL.
2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME.
3. DIMENSIONS ARE IN INCHES.