

HTT1127E

Silicon NPN Epitaxial Twin Transistor

REJ03G0839-0100
 (Previous ADE-208-1540)
 Rev.1.00
 Aug.10.2005


Features

- Include 2 transistors in a small size SMD package: EMFPAK-6 (6 Leads: 1.2 x 0.8 x 0.5 mm)


Q1: Equivalent Buffer transistor	Q2: Equivalent OSC transistor
2SC5700	2SC5849

Outline

RENESAS Package code: PXSF0006LA-A
 (Package name: EMFPAK-6)



Pin Arrangement



1. Collector Q1
2. Emitter Q1
3. Collector Q2
4. Base Q2
5. Emitter Q2
6. Base Q1


Note: Marking is "R".

Absolute Maximum Ratings

(Ta = 25°C)

Item	Symbol	Ratings		Unit
		Q1	Q2	
Collector to base voltage	V _{CBO}	15	15	V
Collector to emitter voltage	V _{CEO}	4	6	V
Emitter to base voltage	V _{EBO}	1.5	1.5	V
Collector current	I _C	50	80	mA
Collector power dissipation	P _C	Total 200*		mW
Junction temperature	T _j	150	150	°C
Storage temperature	T _{stg}	-55 to +150	-50 to +150	°C

Note: *Value on PCB. (FR-4 (13 x 13 x 0.635 mm)).



Q1 Electrical Characteristics

(Ta = 25°C)







Item	Symbol	Min	Typ	Max	Unit	Test conditions
Collector to base breakdown voltage	$V_{(BR)CBO}$	15	—	—	V	$I_C = 10 \mu A, I_E = 0$
Collector cutoff current	I_{CBO}	—	—	0.1	μA	$V_{CB} = 15 V, I_E = 0$
Collector cutoff current	I_{CEO}	—	—	1.0	μA	$V_{CE} = 4 V, R_{BE} = \text{infinite}$
Emitter cutoff current	I_{EBO}	—	—	0.1	μA	$V_{EB} = 0.8 V, I_C = 0$
DC current transfer ratio	h_{FE}	100	120	150	—	$V_{CE} = 1 V, I_C = 5 mA$
Reverse transfer capacitance	C_{re}	—	0.3	0.45	pF	$V_{CB} = 1 V, f = 1 MHz$ Emitter ground
Gain bandwidth product	f_T	10	12	—	GHz	$V_{CE} = 1 V, I_C = 5 mA,$ $f = 1 GHz$
Forward transfer coefficient	$ S_{21} ^2$	13	16	—	dB	$V_{CE} = 1 V, I_C = 5 mA,$
Noise figure	NF	—	1.0	1.7	dB	$f = 900 MHz,$ $\Gamma_S = \Gamma_L = 50 \Omega$

Q2 Electrical Characteristics


(Ta = 25°C)

Item	Symbol	Min	Typ	Max	Unit	Test conditions
Collector to base breakdown voltage	$V_{(BR)CBO}$	15	—	—	V	$I_C = 10 \mu A, I_E = 0$
Collector cutoff current	I_{CBO}	—	—	0.1	μA	$V_{CB} = 15 V, I_E = 0$
Collector cutoff current	I_{CEO}	—	—	0.1	μA	$V_{CE} = 4 V, R_{BE} = \text{infinite}$
Emitter cutoff current	I_{EBO}	—	—	0.1	μA	$V_{EB} = 1.5 V, I_C = 0$
DC current transfer ratio	h_{FE}	90	120	140	—	$V_{CE} = 1 V, I_C = 5 mA$
Reverse transfer capacitance	C_{re}	—	0.50	0.65	pF	$V_{CB} = 1 V, f = 1 MHz$ Emitter ground
Gain bandwidth product	f_T	2.0	4.0	—	GHz	$V_{CE} = 1 V, I_C = 5 mA,$ $f = 1 GHz$
Forward transfer coefficient	$ S_{21} ^2$	7	11	—	dB	$V_{CE} = 1 V, I_C = 5 mA,$
Noise figure	NF	—	1.7	2.3	dB	$f = 900 MHz$ $\Gamma_S = \Gamma_L = 50 \Omega$

Q1 Main Characteristics









www.DataSheet4U.com




Not recommended
for new design

Q2 Main Characteristics




www.DataSheet4U.com



Not recommended for new design

Package Dimensions



Ordering Information

Part Name	Quantity	Shipping Container
HTT1127ERTL-E	5000	φ 178 mm Reel, 8 mm Emboss Taping

Note: For some grades, production may be terminated. Please contact the Renesas sales office to check the state of production before ordering the product.

RENESAS Technology Corp. Sales Strategic Planning Div. Nippon Bldg., 2-6-2, Ohte-machi, Chiyoda-ku, Tokyo 100-0004, Japan

Keep safety first in your circuit designs!

1. Renesas Technology Corp. puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage. Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (i) placement of substitutive, auxiliary circuits, (ii) use of nonflammable material or (iii) prevention against any malfunction or mishap.

Notes regarding these materials

1. These materials are intended as a reference to assist our customers in the selection of the Renesas Technology Corp. product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Renesas Technology Corp. or a third party.
2. Renesas Technology Corp. assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.
3. All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Renesas Technology Corp. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Renesas Technology Corp. or an authorized Renesas Technology Corp. product distributor for the latest product information before purchasing a product listed herein.
The information described here may contain technical inaccuracies or typographical errors.
Renesas Technology Corp. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors.
Please also pay attention to information published by Renesas Technology Corp. by various means, including the Renesas Technology Corp. Semiconductor home page (<http://www.renesas.com>).
4. When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Renesas Technology Corp. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.
5. Renesas Technology Corp. semiconductors are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact Renesas Technology Corp. or an authorized Renesas Technology Corp. product distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use.
6. The prior written approval of Renesas Technology Corp. is necessary to reprint or reproduce in whole or in part these materials.
7. If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination.
Any diversion or reexport contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited.
8. Please contact Renesas Technology Corp. for further details on these materials or the products contained therein.



RENESAS SALES OFFICES

<http://www.renesas.com>

Refer to "<http://www.renesas.com/en/network>" for the latest and detailed information.

Renesas Technology America, Inc.

450 Holger Way, San Jose, CA 95134-1368, U.S.A
Tel: <1> (408) 382-7500, Fax: <1> (408) 382-7501

Renesas Technology Europe Limited

Dukes Meadow, Millboard Road, Bourne End, Buckinghamshire, SL8 5FH, U.K.
Tel: <44> (1628) 585-100, Fax: <44> (1628) 585-900

Renesas Technology Hong Kong Ltd.

7th Floor, North Tower, World Finance Centre, Harbour City, 1 Canton Road, Tsimshatsui, Kowloon, Hong Kong
Tel: <852> 2265-6688, Fax: <852> 2730-6071

Renesas Technology Taiwan Co., Ltd.

10th Floor, No.99, Fushing North Road, Taipei, Taiwan
Tel: <886> (2) 2715-2888, Fax: <886> (2) 2713-2999

Renesas Technology (Shanghai) Co., Ltd.

Unit2607 Ruijing Building, No.205 Maoming Road (S), Shanghai 200020, China
Tel: <86> (21) 6472-1001, Fax: <86> (21) 6415-2952

Renesas Technology Singapore Pte. Ltd.

1 Harbour Front Avenue, #06-10, Keppel Bay Tower, Singapore 098632
Tel: <65> 6213-0200, Fax: <65> 6278-8001

Renesas Technology Korea Co., Ltd.

Kukje Center Bldg. 18th Fl., 191, 2-ka, Hangang-ro, Yongsan-ku, Seoul 140-702, Korea
Tel: <82> 2-796-3115, Fax: <82> 2-796-2145

Renesas Technology Malaysia Sdn. Bhd.

Unit 906, Block B, Menara Amcorp, Amcorp Trade Centre, No.18, Jalan Persiaran Barat, 46050 Petaling Jaya, Selangor Darul Ehsan, Malaysia
Tel: <603> 7955-9390, Fax: <603> 7955-9510