

-100mA/-50V Digital transistors(with built-in resistors)

DTA014TM / DTA014TEB / DTA014TUB

●Features

- 1) Built-in input resistor enables the direct control of base terminal by input voltage without external resistor.
(See equivalent circuit)
- 2) The bias resistors consist of thin-film resistors with complete isolation to allow positive biasing of the input.
They also have the advantage of almost completely eliminating parasitic effects.
- 3) Only the on/off conditions need to be set for operation, making the device design easy.

●Structure

PNP epitaxial planar silicon transistor
(Resistor built-in type)


●Applications

Inverter, Interface, Driver


●Packaging specifications

Type	Package	VMT3	EMT3F	UMT3F
	Packaging Type	Taping	Taping	Taping
	Code	T2L	TL	TL
	Basic ordering unit (pieces)	8000	3000	3000
DTA014TM		○	-	-
DTA014TEB		-	○	-
DTA014TUB		-	-	○

●Dimensions (Unit : mm)



●Equivalent circuit



$R_1 = 10k\Omega$

●Absolute maximum (Ta=25°C)

Parameter	Symbol	Limits(DTA014T□)			Unit
		M	EB	UB	
Collector-base voltage	V_{CBO}	-50			V
Collector-emitter voltage	V_{CEO}	-50			V
Emitter-base voltage	V_{EBO}	-5			mV
Collector current	I_C	-100			mA
Power dissipation *	P_D	150	200		mW
Junction temperature	T_j	150			°C
Range of storage temperature	T_{stg}	-55 to +150			°C

* Each terminal mounted on a reference land

●Electrical characteristics (Ta=25°C)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Test Conditions
Collector-Base breakdown voltage	BV_{CBO}	-50	-	-	V	$I_C=-50\mu A$
Collector-Emitter breakdown voltage	BV_{CEO}	-50	-	-	V	$I_C=-1mA$
Emitter-Base breakdown voltage	BV_{EBO}	-5	-	-	V	$I_E=-50\mu A$
Collector cut-off current	I_{CBO}	-	-	-500	nA	$V_{CB}=-50V$
Emitter cut-off current	I_{EBO}	-	-	-500	nA	$V_{EB}=-4V$
Collector-Emitter saturation voltage	$V_{CE(sat)}$	-	-0.07	-0.15	V	$I_C=-5mA / I_B=-0.5mA$
DC current gain	h_{FE}	100	-	600	-	$V_{CE}=-10V / I_C=-5mA$
Transition frequency *	f_T	-	250	-	MHz	$V_{CE}=-10V / I_E=5mA$ $f=100MHz$
Input resistance	R_1	7	10	13	kΩ	

* Characteristics of built-in transistor

●Electrical characteristics curves




Fig.1 DC Current Gain vs. Collector Current




Fig.2 Collector Saturation Voltage vs. Collector Current

Notes

No copying or reproduction of this document, in part or in whole, is permitted without the consent of ROHM Co.,Ltd.

The content specified herein is subject to change for improvement without notice.

The content specified herein is for the purpose of introducing ROHM's products (hereinafter "Products"). If you wish to use any such Product, please be sure to refer to the specifications, which can be obtained from ROHM upon request.

Examples of application circuits, circuit constants and any other information contained herein illustrate the standard usage and operations of the Products. The peripheral conditions must be taken into account when designing circuits for mass production.

Great care was taken in ensuring the accuracy of the information specified in this document. However, should you incur any damage arising from any inaccuracy or misprint of such information, ROHM shall bear no responsibility for such damage.

The technical information specified herein is intended only to show the typical functions of and examples of application circuits for the Products. ROHM does not grant you, explicitly or implicitly, any license to use or exercise intellectual property or other rights held by ROHM and other parties. ROHM shall bear no responsibility whatsoever for any dispute arising from the use of such technical information.

The Products specified in this document are intended to be used with general-use electronic equipment or devices (such as audio visual equipment, office-automation equipment, communication devices, electronic appliances and amusement devices).

The Products specified in this document are not designed to be radiation tolerant.

While ROHM always makes efforts to enhance the quality and reliability of its Products, a Product may fail or malfunction for a variety of reasons.

Please be sure to implement in your equipment using the Products safety measures to guard against the possibility of physical injury, fire or any other damage caused in the event of the failure of any Product, such as derating, redundancy, fire control and fail-safe designs. ROHM shall bear no responsibility whatsoever for your use of any Product outside of the prescribed scope or not in accordance with the instruction manual.

The Products are not designed or manufactured to be used with any equipment, device or system which requires an extremely high level of reliability the failure or malfunction of which may result in a direct threat to human life or create a risk of human injury (such as a medical instrument, transportation equipment, aerospace machinery, nuclear-reactor controller, fuel-controller or other safety device). ROHM shall bear no responsibility in any way for use of any of the Products for the above special purposes. If a Product is intended to be used for any such special purpose, please contact a ROHM sales representative before purchasing.

If you intend to export or ship overseas any Product or technology specified herein that may be controlled under the Foreign Exchange and the Foreign Trade Law, you will be required to obtain a license or permit under the Law.



Thank you for your accessing to ROHM product informations.
More detail product informations and catalogs are available, please contact us.

ROHM Customer Support System

<http://www.rohm.com/contact/>