



Description

GM7230 of regulators provides all the active functions for a step-down (buck) switching regulator, and drives 3A load with excellent line and load regulation. GM7230's is available in fixed output voltages of 3.3V, 5V, 12V, and a versatile Adjustable output version.

These regulators are simple to use and require a minimum number of external components. Features include internal frequency compensation and a fixed-frequency oscillator. The GM7230 is high-efficiency replacements for popular three-terminal linear regulators, and is requiring a smaller heatsink or even no heatsink.

GM7230 performs well with standard inductors from several manufacturers, and simplifying the design of switchmode power supplies. GM7230 guarantees ±4% tolerance on output voltage within specified input voltages and output load conditions, and ±15% on the oscillator frequency.

External shutdown is included with 80 µA (typical) standby current. The output switch has cycle-by-cycle current limiting as well as thermal shutdown for full protection under fault conditions.

GM7230 operates at a switching frequency of 150 kHz thus allowing smaller sized filter components than what would be needed with lower frequency switching regulators. Available in a standard 5-lead TO-220 package with several different lead bend options, and a 5-lead TO-263 surface mount package.


Features

- ◆ 3.3V, 5V, 12V and Adjustable output versions
- ◆ Adjustable version output voltage range 1.23V to 37V ±4% max over line and load conditions
- ◆ 3A output current
- ◆ Input voltage range up to 40V
- ◆ Requires only 4 external components
- ◆ High efficiency
- ◆ TTL shutdown capability, low power standby
- Low power standby mode, IQ typically 80 UA
- ◆ Thermal shutdown, current limit protection
- Uses standard inductors
- ◆ 150 kHz fixed frequency internal oscillator

Application


Pre-regulator for linear regulators High-efficiency step-down buck regulator On-card/board switching regulators Positive to negative converter (buck-boost)

TYPICAL APPLICATIONS





◆ MARKING INFORMATION & PIN CONFIGURATIONS



ORDERING INFORMATION

Ordering Number	Output Voltage	Package	Shipping
GM7230-ATB5T	Adj	TO-220-5	50 Units / Tube
GM7230-ATB5BT	Adj	TO-220-5B	50 Units / Tube
GM7230-ATA5R	Adj	TO-263-5	800 Units/Tape & Reel
GM7230-ATA5T	Adj	TO-263-5	50 Units / Tube
GM7230-3.3TB5T	3.3	TO-220-5	50 Units / Tube
GM7230-3.3TB5BT	3.3	TO-220-5B	50 Units / Tube
GM7230-3.3TA5R	3.3	TO-263-5	800 Units/Tape & Reel
GM7230-3.3TA5T	3.3	TO-263-5	50 Units / Tube
GM7230-5.0TB5T	5.0	TO-220-5	50 Units / Tube
GM7230-5.0TB5BT	5.0	TO-220-5B	50 Units / Tube
GM7230-5.0TA5R	5.0	TO-263-5	800 Units/Tape & Reel
GM7230-5.0TA5T	5.0	TO-263-5	50 Units / Tube
GM7230-12TB5T	12	TO-220-5	50 Units / Tube
GM7230-12TB5BT	12	TO-220-5B	50 Units / Tube
GM7230-12TA5R	12	TO-263-5	800 Units/Tape & Reel
GM7230-12TA5T	12	TO-263-5	50 Units / Tube
GM7230-15TB5T	15	TO-220-5	50 Units / Tube
GM7230-15TB5BT	15	TO-220-5B	50 Units / Tube
GM7230-15TA5R	15	TO-263-5	800 Units/Tape & Reel
GM7230-15TA5T	15	TO-263-5	50 Units / Tube

^{*} TB5B: Bent and Staggered Leads of TO-220 package

^{**} For detail Ordering Number identification, please see last page.




♦ ABSOLUTE MAXIMUM RATINGS

Rating	Value	Unit
Maximum Supply Voltage	45	V
ON/OFF Pin Input Voltage/ Feed back pin voltage	-0.3 ≤ V ≤ +25	V
Output Voltage to Ground (Steady State)	-1.0	V
Power Dissipation	Internally Limited	-
Storage Temperature Range	-65 to + 150	°C
Maximum Junction Temperature	+150	°C
Operating Temperature Range	-40 ≤ T _J ≤ 125	°C
Minimum ESD Rating (C=100pF, R=1.5k)	2	kV
Lead Temperature (Soldering, 10 sec.)	+260	°C
Lead Temperature S Package Vapor Phase (60 secretary.) Infrared (10 secretary.) T Package (Soldering, 10 secretary.) Maximum Junction Temperature	+215 +245 +260 +150	°C

OPERATING CONDITIONS

Rating	Value	Unit
Temperature Range	45 ≤ T _J ≤+125	°C
Supply Voltage	4.5 to 40	V

BLOCK DIAGRAM



Power Management



GM7230

3A STEP-DOWN VOLTAGE REGULATOR

◆ ELECTRICAL CHARACTERISTICS: GM7230-3.3

(Specifications with standard type face are for T_J = 25°C, and those with **boldface type** apply over full Operating Temperature Range)

Parameter	Conditions	Symbol	Min	Тур	Max	Unit
Output Voltage	$4.75 \le V_{IN} \le 40V, \ 0.2A \le I_{LOAD} \le 3A$	V _{out}	3.168/ 3.135	3.3	3.432/ 3.465	V
Efficiency	$V_{IN} = 12V, I_{LOAD} = 3.0A$		-	73	-	%

◆ ELECTRICAL CHARACTERISTICS: GM7230-5.0

(Specifications with standard type face are for $T_J = 25^{\circ}$ C, and those with **boldface type** apply over full Operating Temperature Range)

Parameter	Conditions	Symbol	Min	Тур	Max	Unit
Output Voltage	$7V \le V_{\text{IN}} \le 40V, \ 0.2A \le I_{\text{LOAD}} \le 3A$	V _{out}	4.800/ 4.750	5.0	5.200/ 5.250	V
Efficiency	$V_{IN} = 12V, I_{LOAD} = 3.0A$		-	80	-	%

♦ ELECTRICAL CHARACTERISTICS: GM7230-12

 $(Specifications \ with \ standard \ type \ face \ are \ for \ T_J = 25^{\circ}C, \ and \ those \ with \ \textbf{boldface type} \ apply \ over \ full \ Operating \ Temperature \ Range)$

Parameter	Conditions	Symbol	Min	Тур	Max	Unit
Output Voltage	$15V \leq V_{\text{IN}} \leq 40V, 0.2A \leq I_{\text{LOAD}} \leq 3A$	V _{out}	11.52/ 11.40	12.0	12.48/ 12.60	V
Efficiency	V _{IN} = 25V, I _{LOAD} = 3.0A		-	90	-	%

♦ ELECTRICAL CHARACTERISTICS: GM7230-ADJ

 $(Specifications \ with \ standard \ type \ face \ are \ for \ T_J = 25^{\circ}C, \ and \ those \ with \ \textbf{boldface type} \ apply \ over \ full \ Operating \ Temperature \ Range)$

Parameter	Conditions \leq	Symbol	Min	Тур	Max	Unit
Feedback Voltage	$4.5V \le V_{\text{IN}} \le 40V, \ 0.2A \le I_{\text{LOAD}} \le 3A$ $V_{\text{OUT}} = 3V$	V_{out}	1.193/ 1.180	1.230	1.267/ 1.280	V
Efficiency	V_{IN} = 12V, I_{LOAD} = 3A, V_{OUT} = 3V		-	73	-	%





♦ ELECTRICAL CHARACTERISTICS: All Output Voltage Versions

(Specifications with standard type face are for $T_J = 25\,^{\circ}$ C, and those with **boldface type** apply over full Operating Temperature Range. Unless otherwise specified, V_{IN} = 12V for the 3.3V, 5.0V and ADJ version and V_{IN} = 24V for 12V version. I_{LOAD} = 500 mA)

Parameter	Conditions	Symbol	Min	Тур	Max	Unit
Feedback Bias Current	V _{FB} = 1.3V (Adjustable Version Only)	l _b	-	10	50 / 100	nA
Oscillator Frequency	(Note 6)	f _o	127/ 110	150	173 / 173	kHz
Saturation Voltage	I _{OUT} = 3A (Notes 7, 8)	V _{SAT}	-	1.16	1.4 / 1.5	V
Max Duty Cycle (ON)	(Note 8)	DC		100	-	%
Min Duty Cycle (OFF)	(Note 9)	DC		0	-	%
Current Limit	Peak Current (Notes 7, 8)	I _{CL}	3.6 / 3.4	4.5	6.9 / 7.5	А
	(Notes 7, 9, 10) Output = 0 V		-	-	50	μΑ
Output Leakage Current	(Notes 10) Output = -0.9V	. I <u>L</u>	-	2	30	mA
Quiescent Current	(Note 9)	ΙQ	-	5	10	mA
Standby Quiescent Current	ON/OFF Pin = 5V (OFF) (Note 10)	I _{STBY}	-	80	200 / 250	μA
Thermal Resistance	TO-220 or TO-263 Package, Junction to Case TO-220 Package, Junction to Ambient (Note 11) TO-263 Package, Junction to Ambient (Note 12) TO-263 Package, Junction to Ambient (Note 13) TO-263 Package, Junction to Ambient (Note 14)	JA JA	- - - -	2 50 50 30 20	- - - -	°C/W
ON/OFF Pin	Low (ON)	V _{IH}	-	1.3	0.6	V
Logic Input Level	High (OFF)	V _{IL}	2.0	1.3	-	V
ON/OFF Die leget Comment	V _{LOGIC} = 2.5V (OFF) V _{LOGIC} = 0.5V (ON)		-	5	15	μΑ
ON/OFF Pill Input Current			-	0.02	5	μΑ


- Note 1: Absolute Maximum Ratings indicate limits beyond which damage to the device may occur. Operating Ratings indicate conditions for which the device is intended to be functional, but do not guarantee specific performance limits. For guaranteed specifications and test conditions, see the Electrical Characteristics.
- Note 2: The human body model is a 100 pF capacitor discharged through a 1.5k resistor into each pin.
- Note 3: Typical numbers are at 25°C and represent the most likely norm.
- Note 4: All limits guaranteed at room temperature (standard type face) and at temperature extremes (bold type face). All room temperature limits are 100% production tested. All limits at temperature extremes are guaranteed via correlation using standard Statistical Quality Control (SQC) methods. All limits are used to calculate Average Outgoing Quality Level (AOQL).
- Note 5: External components such as the catch diode, inductor, input and output capacitors, and voltage programming resistors can affect switching regulator system performance. When the GM7230 is used as shown in the Figure 1 test circuit, system performance will be as shown in system parameters section of Electrical Characteristics.
- Note 6: The switching frequency is reduced when the second stage current limit is activated.
- Note 7: No diode, inductor or capacitor connected to output pin.
- Note 8: Feedback pin removed from output and connected to 0V to force the output transistor switch ON.
- Note 9: Feedback pin removed from output and connected to 12V for the 3.3V, 5V, and the ADJ. version, and 15V for the 12V version, to force the output transistor switch OFF.
- **Note 10:** $V_{IN} = 40V$.
- Note 11: Junction to ambient thermal resistance (no external heat sink) for the TO-220 package mounted vertically, with the leads soldered to a printed circuit board with (1 oz.) copper area of approximately 1 in².
- Note 12: Junction to ambient thermal resistance with the TO-263 package tab soldered to a single printed circuit board with 0.5 in of (1 oz.) copper area.
- Note 13: Junction to ambient thermal resistance with the TO-263 package tab soldered to a single sided printed circuit board with 2.5 in of (1 oz.) copper area.
- Note 14: Junction to ambient thermal resistance with the TO-263 package tab soldered to a double sided printed circuit board with 3 in² of (1 oz.) copper area on Gm7230 side of the board, and approximately 16 in² of copper on the other side of the p-c board.



◆ TEST CIRCUIT AND LAYOUT GUIDELINES

Careful layout is important with any switching regulator. Rapidly switching currents associated with wiring inductance generate voltage transients which can cause problems. To minimize inductance and ground loops, the lengths of the leads indicated by heavy lines in Figure 1 below should be kept as short as possible. Single-point grounding (as indicated in Figure 1) or ground plane construction should be used for best results. When using the Adjustable version, place the programming resistors as close as possible to Gm7230, to keep the sensitive feedback wiring short.

Figure 1(a). Fixed Output Voltage Versions



C_{IN} - 470 µF, 50V, Aluminum Electrolytic


COUT - 220 µF, 25V, Aluminum Electrolytic

D1 - 5A, 40V Schottky

L1 - 68 µH, 3L Electronic Corp. TC-680M-3A-5026



Figure 1(b). Adjustable Output Voltage Versions



$$V_{OUT} = V_{REF} (1 + \frac{R2}{R1})$$

R2 = R1 ($\frac{V_{OUT}}{V_{REF}}$ -1)

where V_{REF} = 1.23V, R1 approximetly 1k , 1%

 C_{IN} - 470 μF , 50V, Aluminum Electrolytic

 C_{OUT} - 220 $\mu\text{F},\,25\text{V},\text{Aluminum Electrolytic}$

D1 - 5A, 40V Schottky


L1 - 68 μ H, 3L Electronic Corp. TC-680M-3A-5026


R1 - 1kΩ, 1%


 V_{OUT} = 5V, R2 = 3.06k Ω , 1%





◆ Typical Performance Characteristics















Power Management






3A STEP-DOWN VOLTAGE REGULATOR

◆ Typical Performance Characteristics







◆ Inductor Selection by Manufacturer's Part Numbe.

Inductor Value	3L Electronic Corp.
47µH	TC-470M-3A-5026
68µH	TC-680M-3A-5026
100µH	TC-101M-3A-5026
150µH	TC-151M-3A-8026
220µH	TC-221M-3A-8026
330µH	TC-331M-3A-8026
470µH	TC-471M-3A-8026
680µH	TC-681M-3A-8026
1000μH	TC-102M-3A-9426
1500µH	TC-152M-3A-9426

3L Electronic Corp., + 886(2) 86659999 Website: www.3lcoil.com.tw


◆ Capacitor Selection by Manufacturer's Part Number

Capacitor Value	Nippon Chemil - Con Corp.
100µF	KY50VB100-MH11
220µF	KY50VB220-MJ16
470µF	KY50VB470-MJ30
680µF	KY50VB680-MK30
1000µF	KY50VB1000-ML25


Nippon Chemi-Con Corp. , +81(3)54367628 Website : www.chemi-con.co.jp



♦ TO-220-5 PACKAGE OUTLINE DIMENSIONS




♦ TO-263-5 PACKAGE OUTLINE DIMENSIONS






♦ TO-220-5B PACKAGE OUTLINE DIMENSIONS



◆ ORDERING NUMBER



Power Management



GM7230

3A STEP-DOWN VOLTAGE REGULATOR

GAMMA Micro, are registered trademarks of GAMMA MICROELECTRONICS INC. GAMMA reserves the right to make changes without further notice to any products herein. Information provided herein is alleged to be exact and consistent and this publication surpasses and replaces all information previously supplied.

GAMMA makes no warranty the suitability of its products for any particular purpose, nor does GAMMA assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability including without limitation special, consequential or incidental damages.

GAMMA products are not authorized for using as critical components in life support devices or systems without prior written approval from GAMMA MICROELECTRONICS INC.