


Phototransistor Output; GaAs Input

Part Number	CTR @		BV _{CEO} (V)	BV _{CBO} (V)	t _{ON} /t _{OFF} (μs)	V _{ISO} AC[RMS]	Pkg Outline		Agency Approvals		
	10mA	I _F (%)					QT	MOT	Standard	VDE 0884	
	min	max	min	min	max	min	max	QT		MOT	
4N25	20	-	30	70	-	5.3kV	K	J	A,B,D,F,N,S,T,U	.300	V
4N26	20	-	30	70	-	5.3kV	K	J	A,B,D,F,N,S,T,U	.300	V
4N27	10	-	30	70	-	5.3kV	K	J	A,B,D,F,N,S,T,U	.300	V
4N28	10	-	30	70	-	5.3kV	K	J	A,B,D,F,N,S,T,U	.300	V
4N35	100	-	30	70	10/10	5.3kV	K	J	A,B,D,F,N,S,T,U	.300	V
4N36	100	-	30	70	10/10	5.3kV	K	J	A,B,D,F,N,S,T,U	.300	V
4N37	100	-	30	70	10/10	5.3kV	K	J	A,B,D,F,N,S,T,U	.300	V
CNW11AV-1	100	300	70	70	15/15	4.0kV	A	N/A	A,B,D,F,N,S,U	.300	N/A
CNW11AV-2	50	-	70	70	15/15	4.0kV	A	N/A	A,B,D,F,N,S,U	.300	N/A
CNW11AV-3	20	-	70	70	15/15	4.0kV	A	N/A	A,B,D,F,N,S,U	.300	N/A
CNW83	40	-	50	70	-	5.9kV	A	N/A	A,B,D,F,N,S,U	.300	N/A
CNW85	63	320	80	120	-	5.9kV	A	N/A	A,B,D,F,N,S,U	.300	N/A
CNX35U	40	160	30	70	20/20	5.3kV	K	N/A	A,B,D,F,N,S,T,U	.300	N/A
CNX36U	80	200	30	70	20/20	5.3kV	K	N/A	A,B,D,F,N,S,T,U	.300	N/A
CNX38U	70	210	80	120	20/20	5.3kV	K	N/A	A,B,D,F,N,S,T,U	.300	N/A
CNX39U	60	100	30	70	20/20	5.3kV	K	N/A	A,B,D,F,N,S,T,U	.300	N/A
CNX83A	40	250	50	70	-	3.75kV	I	N/A	A,B,D,F,N,S,U	.300	N/A
CNY17-1	40	80	70	70	10/10	5.3kV	K	J	A,B,D,F,N,S,T,U	.300	V
CNY17-2	63	125	70	70	10/10	5.3kV	K	J	A,B,D,F,N,S,T,U	.300	V
CNY17-3	100	200	70	70	10/10	5.3kV	K	J	A,B,D,F,N,S,T,U	.300	V
CNY17-4	160	320	70	70	10/10	5.3kV	K	N/A	A,B,D,F,N,S,T,U	.300	N/A
CNY17G-1	40	80	70	70	10/10	3.75kV	I	N/A	A,B,D,F,N,S,U	.300	N/A
CNY17G-2	63	125	70	70	10/10	3.75kV	I	N/A	A,B,D,F,N,S,U	.300	N/A
CNY17G-3	100	200	70	70	10/10	3.75kV	I	N/A	A,B,D,F,N,S,U	.300	N/A
CNY17G-4	160	320	70	70	10/10	3.75kV	I	N/A	A,B,D,F,N,S,U	.300	N/A
H11A1	50	-	30	70	-	5.3kV	K	J	A,B,D,F,N,S,T,U	.300	V
H11A2	20	-	30	70	-	5.3kV	K	N/A	A,B,D,F,N,S,T,U	.300	N/A
H11A3	20	-	30	70	-	5.3kV	K	N/A	A,B,D,F,N,S,T,U	.300	N/A
H11A4	10	-	30	70	-	5.3kV	K	J	A,B,D,F,N,S,T,U	.300	V
H11A5	30	-	30	70	-	5.3kV	K	N/A	A,B,D,F,N,S,T,U	.300	N/A
H11AV1	100	300	70	70	15/15	5.3kV	N/A	J	A,D,F,N,S,T,U	N/A	V
H11AV1A	100	300	70	70	15/15	5.3kV	N/A	J	A,D,F,N,S,T,U	N/A	V
H11AV2	50	-	70	70	15/15	5.3kV	N/A	J	A,D,F,N,S,T,U	N/A	V
H11AV2A	50	-	70	70	15/15	5.3kV	N/A	J	A,D,F,N,S,T,U	N/A	V
MCT2	20	-	30	70	-	5.3kV	K	J	A,B,D,F,N,S,T,U	.300	V
MCT210	150	-	30	30	-	5.3kV	K	N/A	A,B,D,F,N,S,T,U	.300	N/A
MCT2200	20	-	30	70	10/10	5.3kV	K	N/A	A,B,D,F,N,S,T,U	.300	N/A



Notes:

Optocoupler package drawings appear on pages 23, 24 and 25