

50 Amp PLASTIC SILICON AUTOMOTIVE RECTIFIERS

Description

Mechanical Dimensions







Options - Add Suffix to Part #: FR5000L = 2 Leads

For 1 Lead:

FR5000C = Lead On Cathode FR5000A = Lead On Anode

Features


- **LOW COST**
- HIGH SURGE CAPABILITY
- DIFFUSED JUNCTION


- LOW LEAKAGE CURRENT
- **HIGH TEMPERATURE CAPABILITY**
- MEETS UL SPECIFICATION 94V-0


	FR5001 5004 Series				Units
Maximum Ratings	FR5001	FR5002	FR5003	FR5004	
Peak Repetitive Reverse VoltageV _{RRM}	100	200	300	400	Volts
RMS Reverse VoltageV _{R(rms)}	70	140	210	280	Volts
DC Blocking Voltage V_{DC}	100	200	300	400	Volts
Average Forward Rectified Current $I_{F(av)}$ Single Phase Resistive Load, 60 Hz, $T_C = 150$ °C			50		Amps
Non-Repetitive Peak Forward Surge CurrentI _{FSM} Surge Supplied @ Rated Load Conditions, ½ Sine Wave, Single Phase, 60 Hz	600				Amps
Operating & Storage Temperature Range T_J , T_{STRG}	50 to 175				°C
Electrical Characteristics Maximum Forward Voltage @ 80AV _F <i>(Note 4)</i>		1	.06		Volts
Maximum DC Reverse CurrentI _R 25°C @ Rated DC Blocking Voltage 150°C			2.0		μAmp μAmp
Typical Junction CapacitanceC _J (Note 1)		3	00		pF
Typical Thermal ResistanceR _{eJC} (Note 2)).8		°C/W
Typical Reverse Recovery Timet _{RR}		3	3.0		μs





50 Amp PLASTIC SILICON AUTOMOTIVE RECTIFIERS











Ratings at 25 Deg. C ambient temperature unless otherwise specified.

Single Phase Half Wave, 60 Hz Resistive or Inductive Load.

For Capacitive Load, Derate Current by 20%.

NOTES: 1. Measured @ 1 MHz and applied reverse voltage of 4.0V.

- 2. Thermal Resistance Junction to Case, Jedec Method.
- 3. When Mounted to heat sink, from body.
- 4. Pulse Test: Pulse Width ≤ 300 μs, Duty Cycle 2%.