



SSMA Female Connector Solder Attachment 2 Hole Flange For PE-SR405AL, PE-SR405FL, RG405, .328 inch Hole Spacing

TECHNICAL DATA SHEET

PE44437

SSMA Female Connector Solder Attachment 2 Hole Flange For PE-SR405AL, PE-SR405FL, RG405, .328 inch Hole Spacing

Configuration

Connector SSMA Female
Connector Specification MIL-C-39012

Connector Interface Type PE-SR405AL,PE-SR405FL,RG405

Cable Attachment Method (Shield/Contact)

Body Style

Mount Method

Solder/Solder

Straight

2 Hole Flange

Electrical Specifications

Impedance, Ohms 50

Mechanical Specifications

Temperature

Operating Range, deg C -65 to +165

Size

 Length, in [mm]
 0.495 [12.57]

 Width/Dia., in [mm]
 0.19 [4.83]

 Height, in [mm]
 0.469 [11.91]

 Weight, lbs [g]
 0.004 [1.81]

Connector

Type SSMA Female Contact Material and Plating Gold

Contact Plating Specification MIL-G-45204
Body Material and Plating Stainless Steel, Gold
Body Plating Specification MIL-G-45204

Dielectric Type Teflon

Compliance Certifications (visit www.Pasternack.com for current document)
RoHS Compliant
Yes

Plotted and Other Data


Notes: Values at 25 °C, sea level


Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: SSMA Female Connector Solder Attachment 2 Hole Flange For PE-SR405AL, PE-SR405FL, RG405, .328 inch Hole Spacing PE44437

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal.




M	MATERIALS
BODY	STAINLESS STEEL GOLD PLATED
CONTACT	GOLD PLATED
INSULATOR	PTFE





MOUNTIG HOLES



STRIPPING DIMENSION

ASSEMBLY PROCEDURES

- NOT NICK CENTER CONDUCTOR. 1. STRIP CABLE AS SHOWN. DO
 - SOLDER CONTACT TO CENTER CONDUCTOR. 2
- 3. INSERT CABLE INTO BODY UNTIL OUTER CONDUCTOR IS FLUSH WITH BODY SHOULDER. SOLDER OUTER CONDUCTOR TO BODY.



PASTERNACK ENTERPRISES, INC.

P.O BOX 16759, IRVINE, CA 92623 PHONE (949) 261-1920 FAX (949) 261-7451

X.Con	ack.c	S
ternac	astern	TOO
w.pas	les@b	IRFR
W	3S: sa	28.
JORE	ODRES	COAXIAI & FIRER OPTICS
WEB AUDRESS: www.pasternack.con	MAIL ADDRESS: sales@pasternack.c	5
>	~	

SSMA FEMALE, 2 HOLE PANEL MOUNT FOR RG405, PE-SR405AL & PE-SR405FL DES.

SIZE A **FSCM NO. 53919**

NOTES

PE44437

127

SCALE N/A

CAD FILE 123103

1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL.
2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME.